

Application No.: 10/814,992  
Amendment dated: October 10, 2006  
Reply to Office Action of March 30, 2006  
Attorney Docket No.: 56229-153 (ANAK-248)

## B. AMENDMENTS TO THE CLAIMS

This listing of claims will replace all prior versions, and listings, of claims in the application:

### Listing of Claims:

1. (Currently Amended) A method for optimizing radiographic image quality by irradiating the object with x-rays from an x-ray apparatus during an initial period of an x-ray exposure, the x-ray apparatus including an x-ray source configured to generate x-rays directed towards and through said object, the x-ray source including an electron source and an x-ray emissive target, the method comprising:
  - A. determining a first operating voltage level  $kVp_0$  of the x-ray source for initial operation of the x-ray apparatus;
  - B. during a first sampling interval  $\Delta t_1$  in the beginning of the x-ray exposure period, operating the x-ray apparatus at said first operating voltage level  $kVp_0$  and using one or more sensors to detect x-rays that have passed through at least a portion of the object during the interval  $\Delta t_1$ , wherein the first sampling interval  $\Delta t_1$  is relatively small compared to the x-ray exposure period;
  - C. after said first sampling interval  $\Delta t_1$ , processing the output signals from said sensors to determine a second operating voltage level  $kVp_1$ ;
  - D. during a second sampling interval  $\Delta t_2$  within the same x-ray exposure period, operating said x-ray apparatus at said second operating voltage level  $kVp_1$  and using said sensors to detect x-rays that have passed through at least a portion of the object during the interval  $\Delta t_2$ , wherein the second sampling interval  $\Delta t_2$  is relatively small compared to the x-ray exposure period; and
  - E. after said second sampling interval  $\Delta t_2$ , processing the sensor output signals to determine an optimal value  $kVp_2$  for the operating voltage level, and setting the operating voltage level of the x-ray apparatus to said optimal value  $kVp_2$  for the remainder of the x-ray exposure period.
2. (canceled)
3. (canceled)
4. (currently amended) A method in accordance with claim 3, further comprising:  
determining the optimal values of one or more additional x-ray exposure parameters of the

Application No.: 10/814,992  
Amendment dated: October 10, 2006  
Reply to Office Action of March 30, 2006  
Attorney Docket No.: 56229-153 (ANAK-248)

x-ray apparatus, and setting said additional x-ray exposure parameters to said optimal values for the remainder of the x-ray exposure period.

5. (original) A method in accordance with claim 4, wherein said additional x-ray exposure parameters comprise at least one of: x-ray tube current (mA), size of focal spot, and number and type of soft x-ray filters; and wherein said x-ray tube current is the current formed by electrons emitted from said electron source, said focal spot is the area within said target upon which the electrons impinge, and said soft x-ray filters are filters for absorbing soft x-ray radiation.

6. (canceled)

7. (original) A method in accordance with claim 1, wherein said object comprises anatomical tissue of a patient, and wherein said optimal value of said operating voltage are chosen so that the patient's exposure to x-rays is substantially minimized when the x-ray apparatus is operated at said optimal value.

8. (original) A method in accordance with claim 2, wherein said x-ray imaging system comprises one of: a) a radiographic film defining an image plane; and b) a flat panel detector configured to detect x-rays that have passed through said object, said flat panel detector being disposed along an image plane.

9. (original) A method in accordance with claim 8, wherein said one or more sensors are positioned between said object and said image plane.

10. (original) A method in accordance with claim 9, wherein a plurality of sensors are used to detect x-rays during said first and second sampling intervals, and wherein each of said plurality of sensors are positioned at different locations so that said sensors can detect x-rays that have traversed different portions of said object.

11. (original) A method in accordance with claim 1, wherein said object comprises anatomical tissue of a patient, and further comprising the step of measuring the thickness of said tissue before the step of determining said first and second operating voltage levels.

12. (original) A method in accordance with claim 11, wherein the step of determining said optimal value of said operating voltage level comprises:

Application No.: 10/814,992  
 Amendment dated: October 10, 2006  
 Reply to Office Action of March 30, 2006  
 Attorney Docket No.: 56229-153 (ANAK-248)

A. calculating the differential attenuation coefficient  $\Delta\mu$  of the exposed tissue at said voltage level  $kVp_1$ , based on the output signals from said sensors, and based on the measured thickness of said tissue;

B. creating at least one  $\Delta\mu$  table for at least one region of said object;

C. determining the composition of said tissue using said calculated value of  $\Delta\mu$ , and said at least one  $\Delta\mu$  table; and

D. determining said optimal value of said operating voltage level, using said tissue composition and said  $\Delta\mu$  table.

13. (original) A method in accordance with claim 12, wherein at least one  $\Delta\mu$  table is created in step B for every centimeter of breast tissue, and wherein each of said at least one  $\Delta\mu$  table defines at least two kVp values for said sampling intervals, and at least three  $\Delta\mu$  values for at least three breast tissue compositions.

14. (original) A method in accordance with claim 4, wherein determining said optimal values of said additional x-ray parameters comprises:

A. calculating the differential attenuation coefficient  $\Delta\mu$  of the exposed tissue at said voltage level  $kVp_1$ , based on the output signals from said sensors, and based on the measured thickness of said tissue;

B. creating at least one  $\Delta\mu$  table for at least one region of said object;

C. determining the composition of said tissue using said calculated value of  $\Delta\mu$ , and said at least one  $\Delta\mu$  table; and

D. determining said optimal values of said additional x-ray parameters using said tissue composition and said  $\Delta\mu$  table.

15. (original) A method in accordance with claim 1, wherein steps B and C are repeated for a plurality of n sampling intervals  $\Delta t_1^1, \dots, \Delta t_1^n$ , during which the x-ray apparatus is operated at corresponding operating voltage levels  $kVp_1^1, \dots, kVp_1^n$ , so that said optimal operating voltage level  $kVp_2$  is determined based on sensor output signals generated while the x-ray apparatus was operated at voltage level  $kVp_1^n$  during a sampling interval  $\Delta t_1^n$ .

16. (currently amended) An x-ray imaging apparatus, the x-ray imaging apparatus comprising:

an x-ray source adapted to generate x-rays directed towards and through an object,  
the x-ray source including an electron source configured to emit electrons, and an x-ray

Application No.: 10/814,992  
Amendment dated: October 10, 2006  
Reply to Office Action of March 30, 2006  
Attorney Docket No.: 56229-153 (ANAK-248)

emissive target configured to emit x-rays from a focal spot within the target in response to incident electrons that have been accelerated from said electron source toward said target at an operating voltage of said x-ray source;

an x-ray imaging system configured to receive x-rays that have been emitted from said x-ray source and that have passed through said object, and to generate an image of said object from the received x-rays;

one or more sensors disposed between the object and said x-ray imaging system, said sensors being configured to detect x-rays from said x-ray source that have traversed said object during a first sampling period  $\Delta t_1$  and a second sampling period  $\Delta t_2$ , and to generate one or more output signals representative of the attenuated intensity of the detected x-rays, wherein the first sampling period and the second sampling period are each relatively small compared to the total exposure time during which said object is exposed to radiation generated by said x-ray source;

a processor configured to determine a first operating voltage level kVp<sub>0</sub> of the x-ray source for an initial operation of said x-ray apparatus during said first sampling period  $\Delta t_1$ , said processor being further configured to calculate, after said first sampling period  $\Delta t_1$ , a second operating voltage level kVp<sub>1</sub> of the x-ray source by processing the output signals generated by said sensors during said first sampling period, said processor being further configured to calculate, after said second sampling period  $\Delta t_2$ , an optimal operating voltage level kVp<sub>2</sub> of the x-ray source by processing the output signals generated by said sensors during said second sampling period; and

a controller configured to adjust the operating voltage of said ~~x-ray apparatus~~source to said first and second operating voltage levels during said first and second sampling periods, respectively, said controller being further configured to adjust, after said second sampling period  $\Delta t_2$ , the operating voltage of said ~~x-ray apparatus~~source to said optimal voltage level kVp<sub>2</sub> for the remainder of said x-ray exposure period.

17. (canceled)

18. (currently amended) An x-ray apparatus in accordance with claim ~~17~~16, wherein said processor is further configured to determine the optimal values of one or more x-ray exposure parameters, and wherein said x-ray exposure parameters include at least one of operating voltage (kVp), current (mA), and size of focal spot;

~~wherein the operating voltage is the accelerating voltage between said electron source and said x-ray target for accelerating electrons emitted from said electron source~~

Application No.: 10/814,992  
Amendment dated: October 10, 2006  
Reply to Office Action of March 30, 2006  
Attorney Docket No.: 56229-153 (ANAK-248)

~~toward said x-ray target, and~~

wherein the current is formed by said electrons emitted from said electron source.

19. (canceled)

20. (original) An x-ray apparatus in accordance with claim 16, wherein said x-ray imaging system comprises one of: a) a radiographic film defining an image plane; and b) a flat panel detector disposed along an image plane and configured to detect x-rays that have passed through the object.

21. (original) An x-ray apparatus in accordance with claim 16, wherein said one or more sensors comprise at least one of: an ionization chamber; a scintillator; and a solid state detector.

22. (original) An x-ray apparatus in accordance with claim 16, wherein the object comprises anatomical tissue, and wherein said processor comprises:

- A. means for calculating the thickness of the object;
- B. means for calculating the differential attenuation coefficient of the tissue at each of said first and second kVp levels based on the output signals from said sensors and based on the measured thickness of said tissue;
- C. means for providing at least one  $\Delta\mu$  table for at least one region of said object; and
- D. means for computing said optimal values of said x-ray exposure parameters using said  $\Delta\mu$  table.